

DeesLink

Remote Access Unit

Model 340

*Access to your communications equipment,
from anywhere at any time.*

Special Features and Functions

- All features & functions are programmable
- Remote and local programming through DTMF telephone
- Multiple Users profile assignments (8)
- Two outputs, Ports A & B
- User Port Assignment
- Programmable restricted dialing assigned per User
- 8 Programmable Passwords, up to 8 digits long
- Non Volatile memory
- PSTN accessible
- Equipped with plug-in power supply
- Modular jack connections

*DeesLink is your
path into the office
while you're away.*

DeesLink is a secure, multiuser, programmable remote access unit; which allows password protected dial access by off-premise users to your communication system.

DeesLink assures access to your office communications systems and can be controlled with complete protection against unauthorized use.

With DeesLink you can allow multiple users access to your communications systems, each with their own individual profiles. Accessibility and user features are programmed as user profiles in non-volatile memory.

DeesLink supports one user at a time, but allows up to 8 different user profiles.

User Profiles

Each user profile is a unique set of individual parameters that set the following characteristics for each user: port they will be connected to, lower and upper line numbers they can dial, and the time out period. User profiles are assigned and programmable.

Programming

The system administrator is the only user (User #1) with permission to program or reprogram unit.

DeesLink can be programmed locally through a tone dialing telephone, or remotely by dialing into the unit and entering the programming mode.

Passwords

Passwords are unique to each user, and necessary before DeesLink will connect the user to the auxillary systems. Each password has to be a minimum of 4 digits long but can be up to a maximum of 8 digits.

The user profile identifies what Port the user will be connected to upon access.

Restricted Dialing

Once the user has successfully accessed either of the Ports and is ready to dial a line number on the auxillary system, their user profile determines what numbers they are allowed to dial.

User Time Out Period & Release

A user can disconnect from the DeesLink by entering ##, or just hanging up. In the event the user forgets to enter ##, the unit will automatically disconnect after the preset Time Out Period.

(1 — 99 minutes). The default is 99 minutes, or can be programmed differently for each user.

Remote call monitoring is a very important application for DeesLink. Coupled with one of the CM call monitoring systems, remote access can be offered to as many as 8 different clients. DeesLink assures their access to only those lines assigned in their profiles. Call 1-800-654-5604 to discuss your specific application.

Specifications

Power	24VDC@250ma
Connections	RJ-11 jacks
Dimensions	4x4x1.5 inches
Weight	1.5 lbs

